

音乐.乐无眼


Model No.:RC-BT

English Bluetooth Earphone Replacement Cables User Guide

Buttons and Ports Labeled A. Vol+/Previous track (hold) B. Indicator (Red/Blue Light) C. Power on/off/Pair/Play/Pause/Call D. Vol-/Next track (hold) E. Micro USB Charging Port G. Cable Clip H. MMCX Connector I、Battery

简体中文 蓝牙耳机线使用说明书

产品接口介绍	
A、音量+/上一曲(长按)	
B、状态指示灯(红、蓝灯)	
C、开关机/配对/播放/暂停/通话	
D、音量-/下一曲(长按)	
E、Micro USB充电口	
F、麦克风	
G、线扣	



English Bluetooth Earphone Replacement Cables User Guide

х 1рс

х 1рс

1. Power On: Hold the ● button for 3 seconds, the indicator flashes

blue 3 times; the FB1 powers on after the notification tone.

2. Power Off: Hold the ● button for 3 seconds, the indicator lights

red for 2 seconds; the RC-BT powers off after the notification tone.

indicator flashes red and blue simultaneously and the notification

If it's not connected to any device for 10 minutes after powering on

or disconnect from the device, the RC-BT will power off automatically

3. Reset: Hold the ▲ button for 3 seconds when charging; the

List of items included in the package

1. RC-BT

USB charging cable
 User guide

4. Warranty card

Carrying case

A. Powering On/Off

How to Use

tone rings.

to save power.

简体中文 蓝牙耳机线使用说明书

包装清单	
1、RC-BT	x1条
2、USB充电线	x1条
3、说明书	x1本
4、售后维修卡	x1本
5、收纳包	×1↑
使用说明	

1. Pairing with Bluetooth smart phone

the pairing mode.

使用说明

(一)、开机/关机 开机:按住●键约3秒,蓝灯快闪三次,耳机响起提示音。 关机:按住●键约3秒,红灯常亮2秒后关机,耳机响起提示音。 复位:充电状态下,长按▲键约3秒,红蓝灯同时闪烁且有提示音响 注意:若开机后或与设备断开连接后10min内未连接到任何设备, RC-BT会自动关机,以节省电量。 (二)、配对/连接 与蓝牙手机配对 在连接蓝牙手机使用之前,需令RC-BT与蓝牙手机配对,步骤如下:

1、RC-BT关机状态下,按住●键约5秒,红蓝灯交替闪烁时松开,进

English Bluetooth Earphone Replacement Cables User Guide

Before used with the Bluetooth smart phone, the RC-BT should be

paired with the smart phone with following steps:

1) While the RC-BT is powered off, hold the ● button for 5 seconds until the indicator flashes blue and red alternately; the RC-BT enters

2) Turn on the Bluetooth function on the smart phone and search for Bluetooth devices. Choose "RC-BT" to pair with it.

●关闭一配二功能:待机未连接设备时,同时按●键和▼键约4秒,听 到提示音后释放。 ●开启一配二功能: 待机未连接设备时, 同时按●键和▲键约4秒, 听 到提示音后释放。

3.从设备一上操作,选择连接RC-BT。此时,RC-BT已经同时连接了

2、开启手机蓝牙功能,搜索蓝牙设备。选择"RC-BT"即可配对

同时连接两个蓝牙设备,操作方法如下: 1.首先将RC-BT与设备一配对连接。 2.重启RC-BT并进入配对模式,与设备二配对连接。

蓝牙耳机线使用说明书

(三)、通话

1、基本通话操作 取消呼叫:短按●键一次 接听来电:短按●键一次 拒接来电:长按●键约2秒

简体中文

入配对模式。

设备一和设备二。

English Bluetooth Earphone Replacement Cables User Guide

C. Making Phone Calls

2. Pairing with two Bluetooth devices simultaneously (One-to-two

1) Pair the RC-BT with Device 1 2) Restart the RC-BT and enter pairing mode to pair with Device 2 $\,$ 3) Choose "RC-BT" to connect on Device 1. Once done, the RC-BT would be connected to the both devices simultaneously already.

a) How to turn off one-to-two mode: When it's in sleep mode and not connecting to any device, hold

and

simultaneously for about 4 seconds until the notification tone is heard.

b) How to turn on one-to-two mode: When it's in sleep mode and not connecting to any device, hold ● and ▲ simultaneously for about 4 seconds until the notification tone is heard.

1. Basic Operation
Cancel the dialing: Press ● button briefly once
Answer a call: Press ● button briefly once
Decline a call: Hold ● button for 2 seconds
End a call: Press ● button briefly once Volume up: Press ▲ button briefly Volume down: Press ▼ button briefly

Volume down: Press ▼ button briefly

Switch the call to the Phone: Hold ● button for 2 seconds

Switch the call to the RC-BT: Hold ● button for 2 seconds

Mute the microphone: Hold ▲ button for 2 seconds Unmute the microphone: Hold ▲ button for 2 seconds

Last number redial: Double press ● button 2.Three-way calling End the first call and answer the new one: Press ● button briefly once Put the first call on hold and answer the new one: Double press ● button

蓝牙耳机线使用说明书

结束通话:短按●键一次 增加音量:短按▲键 减少音量:短按▼键 通话传手机:长按●键约2秒 通话传耳机:长按●键约2秒 麦克风静音:长按▲键约2秒 取消麦克风静音:长按▲键约2秒 末码重拨:双击●键

2、三方诵话操作 接听新来电挂断当前通话:短按●键一次 接听新来电保留当前通话:双击●键

简体中文

通话切换:双击●键 结束当前通话切至保留的通话:短按●键一次

3、连接两个手机通话 挂断第一个手机通话,接通第二个手机来电:短按●键一次保留第一个手机通话,接通第二个手机来电:双击●键 切换通话:双击●键 挂断当前通话,回到被保留的手机:短按●键一次

Switch between calls: Double press ● button

Press ● button briefly once

Double press ● button

Indicator

Press ● button briefly once

End the second call and switch to the call on hold:

3. Answer phone calls when connected to two phones

End the current call and switch to the call on hold:

Pairing mode: Flash blue and red alternately

Charging: Red light stays steadily on

End the call on the first phone and answer the new call on the second phone: Press • button briefly once

Put the call on the first phone on hold and answer the new call on the second phone: Double press • button
Switch between calls from different phones:

Not connecting to any device: Flash blue twice every 2 seconds Connected successfully: Flash blue once every 2.5 seconds Low battery: Flash red

简体中文 蓝牙耳机线使用说明书

指示灯 配对状态:红蓝灯交替闪烁

未连接设备:蓝灯每每2秒快闪2次 已连接设备:蓝灯每2.5秒闪1次 正在充电:红灯恒亮

了解更多

若要了解有关产品信息请访问网址:www.fiio.net

English Bluetooth Earphone Replacement Cables User Guide

To learn more about the product, please visit our website: www.fiio.net.

*Qualcomm aptX is a product of Qualcomm Technologies

International, Ltd.

Qualcomm is a trademark of Qualcomm Incorporated, registered in the United States and other countries, used with permission.aptX is a trademark of Qualcomm Technologies International, Ltd., registered in the United States and other countries, used with permission.